

Classe Legacy Omega Fuse Chart

Classe Legacy & Omega Models Fuse Chart (120V units only)						
Model	Main AC	Rail	Mosfet	Mosfet Alt.	Control Board	Standby
CA-100	MDL-6	GDB-4 x 4	--	--	--	--
CA-101	MDL-6	GDB-4 x 4	--	--	--	--
CA-150	MDL-8	GDB-5 x 4	224.500 x 4*	225.500 x 4*	--	--
CA-151	MDL-8	GDB-5 x 4	224.500 x 4*	225.500 x 4*	--	--
CA-200 Rear Heatsink Oldest	MDA-10	GDB-8 x 4	224.500 x 4*	--	--	--
CA-200 Rear Heatsink	MDA-10	GDB-8 x 4	225.500 x 4	--	--	--
CA-200 Side Heatsink	MDA-10	GDB-8 x 4	225.500 x 4	--	225.750	--
CA-201	MDA-10	GDB-8 x 4	225.500 x 4	--	225.750	--
CA-300	MDA-12	GDB-12 x 4*	224.750 x 4*	225.750 x 4*	--	--
CA-301	MDA-12	--	--	225.750 x 4	225.500	--
CA-400	MDA-15	GDB-16 x 4*	224.750 x 4*	225.750 x 4*	--	--
CA-401	MDA-15	--	225.750 x 4	--	225.500	--
CAM-200	MDL-5	--	--	--	225.500	--
CAM-350	MDA-10	--	225.750 x 4	--	225.500	--
CAP-80	GDC-4	GDB-4 x 4*	225.500 x 2*	--	225.750	--
CAP-100	GDC-4	GDB-4 x 4	225.500 x 4	--	225.750	--
CAP-101	GDC-4	GDB-4 x 4*	225.500 x 2*	--	225.750	--
CAP-150	GDC-5	GDB-4 x 4	225.500 x 4	--	225.750	--
CAP-151 External Fuse	MDL-5	--	--	--	225.750	--
CAP-151 Internal Fuse	GDC-5	GDB-4 x 4	225.500 x 4	--	225.750	--
CAV-75	MDL-6	GDB-3.15 x 12	225.750 x 2*	--	225.500	--
CAV-150	MDL-8	GDB-5 x 12	224.500 x 12*	225.500 x 12*	225.750	--
CAV-180	MDA-10	--	--	--	218.400	--
CAV-500	MDA-12	--	225.750 x 10	--	225.500	--
CD/DVD-1	GDC-2	--	--	--	--	218.063
CDP-.3	218.400	--	--	--	--	218.063
CDP-.5	MDL-3/8	--	--	--	--	--
CDP-1	MDL-3/8	--	--	--	--	--
CDP-1.5	218.400	--	--	--	--	218.063

Classe Legacy Omega Fuse Chart

Classe Legacy & Omega Models Fuse Chart (120V units only)						
Model	Main AC	Rail	Mosfet	Mosfet Alt.	Control Board	Standby
CDP-10	GDC-1	--	--	--	--	--
CDP-100	GDC-1	--	--	--	--	--
CDT-1	MDL-3/8	--	--	--	--	--
CP-35	GDB-3.15	--	--	--	--	--
CP-40	MDA-1	--	--	--	--	--
CP-45	GDB-3.15	--	--	--	--	--
CP-47.5	GDB-3.15	--	--	--	--	--
CP-50	GDB-3.15	--	--	--	--	--
CP-60	GDC-4	--	--	--	--	--
CP-65	GDC-2	--	--	--	--	225.500
CT-10	GDC-1	--	--	--	--	--
DAC-1	MDL-3/8	--	--	--	--	--
DR-2	--	--	--	--	--	--
DR-3	--	--	--	--	--	--
DR-4	MDA-1	--	--	--	--	--
DR-5	MDA-1	--	--	--	--	--
DR-6	MDA-1	--	--	--	--	--
DR-7	--	--	--	--	--	--
DR-8	MDL-5	--	--	--	--	--
DR-9	MDA-10	--	--	--	--	--
DR-10	MDL-5	--	--	--	--	--
DR-15	MDA-10	--	--	--	--	--
DR-25	MDA-12	--	--	--	--	--
M-700	MDA-12	--	--	--	--	--
M-1000	MDA-12	--	--	--	--	--
MODEL 4	MDA-1	--	--	--	--	--
MODEL 5	MDA-1	--	--	--	--	--
MODEL 6	MDA-1	--	--	--	--	--
MODEL 7	--	--	--	--	--	--

Classe Legacy Omega Fuse Chart

Classe Legacy & Omega Models Fuse Chart (120V units only)						
Model	Main AC	Rail	Mosfet	Mosfet Alt.	Control Board	Standby
MODEL 8	MDL-5	--	--	--	--	--
MODEL 9	MDA-10	--	--	--	--	--
MODEL 10	MDL-5	--	--	--	--	--
MODEL 15	MDA-10	--	--	--	--	--
MODEL 20	MDA-1	--	--	--	--	--
MODEL 25	MDA-12	--	--	--	--	--
MODEL 30	MDA-1	--	--	--	--	--
MODEL 70	MDL-5	--	--	--	--	--
S-700	MDA-12	--	--	--	--	--
S-1000	--	--	--	--	--	--
Omega Mono Old Style	MDA-15	--	218.400	--	--	--
Omega Mono New Style	MDA-15	--	218.400	218.800	--	--
Omega Preamplifier MkI-III	MDL-4	--	--	--	--	--
Omega Stereo	MDA-15 x 2	--	225.750 x 2	--	225.001	--
Omega SACD-1	GDC-1	--	--	--	--	--
Omega SACD-2	GDC-1	--	--	--	--	--
Omicron Mono	MDA-12	--	218.400	--	--	--
Omicron Stereo	MDA-15 x 2	--	225.750 x 2	--	225.001	--
SSP-25	MDL-1A	--	--	--	--	--
SSP-30	--	--	--	--	--	--
SSP-50	MDL-1A	--	--	--	--	--
SSP-60	218.400	--	--	--	--	--
SSP-75	GDB-3.15	--	--	--	--	--

* Fuses may not be present in all versions of this model

GDB, GDC, MDA, MDL Fuses manufactured by Bussman.

218.xxx, 224.xxx, 225.xxx Fuses manufactured by Littelfuse

Bussman Fuse Name	Type	Size
MDA-1A	1A 250V SLO-BLOW CERAMIC FUSE	AGC
MDA-10A	10A 250V SLO-BLOW CERAMIC FUSE	AGC
MDA-12A	12A 250V SLO-BLOW CERAMIC FUSE	AGC
MDA-15A	15A 250V SLO-BLOW CERAMIC FUSE	AGC
MDL-1/2A	1/2A 250V SLO-BLOW FUSE	AGC
MDL-3/8A	3/8A 250V SLO-BLOW FUSE	AGC
MDL-1A	1A 250V SLO-BLOW FUSE	AGC
MDL-4A	4A 250V SLO-BLOW FUSE	AGC
MDL-5A	5A 250V SLO-BLOW FUSE	AGC
MDL-6A	6A 250V SLO-BLOW FUSE	AGC
MDL-8A	8A 250V SLO-BLOW FUSE	AGC
GDB-3.15A	3.15A 250V FAST BLOW FUSE	GMA
GDB-4A	4A 250V FAST BLOW FUSE	GMA
GDB-5A	5A 250V FAST BLOW FUSE	GMA
GDB-8A	8A 250V FAST BLOW FUSE	GMA
GDB-12A	12A 250V FAST BLOW FUSE	GMA
GDB-16A	16A 250V FAST BLOW FUSE	GMA
GDC-1A	1A 250V SLO-BLOW FUSE	GMA
GDC-2A	2A 250V SLO-BLOW FUSE	GMA
GDC-3.15A	3.15A 250V SLO-BLOW FUSE	GMA
GDC-4A	4A 250V SLO-BLOW FUSE	GMA
GDC-5A	5A 250V SLO-BLOW FUSE	GMA
Littelfuse Name		
224.500	1/2A 250V FAST ACTING FUSE	Miniature
224.750	3/4A 250V FAST ACTING FUSE	Miniature
225.001	.001A 250V FAST ACTING FUSE	Miniature
225.500	1/2A 250V FAST ACTING FUSE	Miniature
225.750	3/4A 250V FAST ACTING FUSE	Miniature