

The Classé CDP-100 uses RC6 protocol for infrared communications. The following list of infrared codes can be used to program a universal or learning remote control. The Classé Remote Control uses a frequency of 56.0 kHz. Please refer to your remote control's user manual for information on how to program your remote control.

Sys code	IR code	Action
020	0	Number "0"
020	1	Number "1"
020	2	Number "2"
020	3	Number "3"
020	4	Number "4"
020	5	Number "5"
020	6	Number "6"
020	7	Number "7"
020	8	Number "8"
020	9	Number "9"
020	12	Toggle Standby/Operate
200	13	Toggle Mute/Unmute
020	14	Info (go to Status screen)
020	15	Cycle through display intensities (low/medium/high)
200	16	Volume up (volume +)
200	17	Volume down (volume -)
020	18	Cycle through time display modes
020	28	Shuffle play
020	29	Cycle through repeat modes (none, track, disc)
020	32	Go to next track (skip next)
020	33	Go to previous track (skip previous)
020	42	Scan forward
020	43	Scan backward
020	44	Play
020	48	Pause
020	49	Stop
200	56	Function key F1
200	57	Function key F2
020	58	Clear programmed play list (revert to CD's table of contents)
020	59	Program A/B
020	60	Empty playlist
020	66	Open/Close CD tray

020	68	Program mode (go to Program screen)
020	84	Menu
020	85	Home
020	88	Step up (navigate up, +)
020	89	Step down (navigate down, -)
020	90	Step left (navigate left)
020	91	Step right (navigate right)
020	92	Enter
020	120	Number "10"
200	134	Function key F3
200	135	Function key F4
020	150	Set unit in Operate (turn unit on)
020	151	Set unit in Standby (turn unit off)
200	152	Set Mute mode on (mute)
200	153	Set Mute mode off (unmute)

CDP-100 HEX CODES

RC6 MODE 0, SYSTEM CODE 020

IR CODE 0 TOGGLE 0	0
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 0 TOGGLE 1	0
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 1 TOGGLE 0	1
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275	
IR CODE 1 TOGGLE 1	1
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275	
IR CODE 2 TOGGLE 0	2
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
IR CODE 2 TOGGLE 1	2
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
IR CODE 3 TOGGLE 0	3
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275	
IR CODE 3 TOGGLE 1	3
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275	

CDP-100 HEX CODES

IR CODE 4 TOGGLE 0	4
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 4 TOGGLE 1	4
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 5 TOGGLE 0	5
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275	
IR CODE 5 TOGGLE 1	5
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275	
IR CODE 6 TOGGLE 0	6
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
IR CODE 6 TOGGLE 1	6
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
IR CODE 7 TOGGLE 0	7
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 7 TOGGLE 1	7
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 8 TOGGLE 0	8
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C	

CDP-100 HEX CODES

IR CODE 8 TOGGLE 1	8
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C	
IR CODE 9 TOGGLE 0	9
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	
IR CODE 9 TOGGLE 1	9
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	
IR CODE 12 TOGGLE 0	STANDBY/OPERATE
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C	
IR CODE 12 TOGGLE 1	STANDBY/OPERATE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C	
IR CODE 14 TOGGLE 0	INFO
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C	
IR CODE 14 TOGGLE 1	INFO
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C	
IR CODE 15 TOGGLE 0	CYCLE DISPLAY INTENSITY
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	
IR CODE 15 TOGGLE 1	CYCLE DISPLAY INTENSITY
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	

CDP-100 HEX CODES

IR CODE 18 TOGGLE 0	CYCLE TIME DISPLAY
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C	
IR CODE 18 TOGGLE 1	CYCLE TIME DISPLAY
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C	
IR CODE 28 TOGGLE 0	SHUFFLE
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 28 TOGGLE 1	SHUFFLE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 29 TOGGLE 0	REPEAT
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0032 1275	
IR CODE 29 TOGGLE 1	REPEAT
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0032 1275	
IR CODE 32 TOGGLE 0	NEXT TRACK
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 32 TOGGLE 1	NEXT TRACK
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 33 TOGGLE 0	PREVIOUS TRACK
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 1275	

CDP-100 HEX CODES

IR CODE 33 TOGGLE 1	PREVIOUS TRACK
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 1275	
IR CODE 42 TOGGLE 0	SCAN FORWARD
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 125C	
IR CODE 42 TOGGLE 1	SCAN FORWARD
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 125C	
IR CODE 43 TOGGLE 0	SCAN BACKWARD
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 0019 0019 1275	
IR CODE 43 TOGGLE 1	SCAN BACKWARD
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275	
IR CODE 44 TOGGLE 0	PLAY
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 125C	
IR CODE 44 TOGGLE 1	PLAY
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C	
IR CODE 48 TOGGLE 0	PAUSE
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 125C	
IR CODE 48 TOGGLE 1	PAUSE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 125C	

CDP-100 HEX CODES

IR CODE 49 TOGGLE 0	STOP
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 1275	
IR CODE 49 TOGGLE 1	STOP
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 1275	
IR CODE 58 TOGGLE 0	CLEAR PROGRAMMED LIST
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 125C	
IR CODE 58 TOGGLE 1	CLEAR PROGRAMMED LIST
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 125C	
IR CODE 59 TOGGLE 0	PROGRAM A/B
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 1275	
IR CODE 59 TOGGLE 0	PROGRAM A/B
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 1275	
IR CODE 60 TOGGLE 0	EMPTY PLAYLIST
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 60 TOGGLE 1	EMPTY PLAYLIST
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 66 TOGGLE 0	OPEN/CLOSE CD TRAY
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	

CDP-100 HEX CODES

IR CODE 66 TOGGLE 1	OPEN/CLOSE CD TRAY
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
IR CODE 68 TOGGLE 0	PROGRAM MODE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 68 TOGGLE 1	PROGRAM MODE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 84 TOGGLE 0	MENU
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C	
IR CODE 84 TOGGLE 1	MENU
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C	
IR CODE 85 TOGGLE 0	HOME
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 0031 0032 1275	
IR CODE 85 TOGGLE 1	HOME
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 1275	
IR CODE 88 TOGGLE 0	CURSOR UP
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 88 TOGGLE 1	CURSOR UP
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	

CDP-100 HEX CODES

IR CODE 89 TOGGLE 0	CURSOR DOWN
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275	
IR CODE 89 TOGGLE 1	CURSOR DOWN
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275	
IR CODE 90 TOGGLE 0	CURSOR LEFT
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C	
IR CODE 90 TOGGLE 1	CURSOR LEFT
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C	
IR CODE 91 TOGGLE 0	CURSOR RIGHT
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275	
IR CODE 91 TOGGLE 1	CURSOR RIGHT
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275	
IR CODE 92 TOGGLE 0	ENTER
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 92 TOGGLE 1	ENTER
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 120 TOGGLE 0	10
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	

CDP-100 HEX CODES

IR CODE 120 TOGGLE 1	10
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 125C	
IR CODE 150 TOGGLE 0	OPERATE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C	
IR CODE 150 TOGGLE 1	OPERATE
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C	
IR CODE 151 TOGGLE 0	STANDBY
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275	
IR CODE 151 TOGGLE 1	STANDBY
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275	

RC6 MODE 0, SYSTEM CODE 200

IR CODE 13 TOGGLE 0	MUTE TOGGLE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275	
IR CODE 13 TOGGLE 1	MUTE TOGGLE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275	
IR CODE 16 TOGGLE 0	VOLUME UP
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C	

CDP-100 HEX CODES

IR CODE 16 TOGGLE 1	VOLUME UP
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 17 TOGGLE 0	VOLUME DOWN
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	
IR CODE 17 TOGGLE 1	VOLUME DOWN
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	
IR CODE 56 TOGGLE 0	F1
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 56 TOGGLE 1	F1
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 57 TOGGLE 0	F2
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 1275	
IR CODE 57 TOGGLE 1	F2
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 1275	
IR CODE 134 TOGGLE 0	F3
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
IR CODE 134 TOGGLE 1	F3
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	

CDP-100 HEX CODES

IR CODE 135 TOGGLE 0	F4
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 135 TOGGLE 1	F4
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 152 TOGGLE 0	MUTE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 152 TOGGLE 1	MUTE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 153 TOGGLE 0	UNMUTE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275	
IR CODE 153 TOGGLE 1	UNMUTE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275	