

The Classé CP-800 uses RC6 protocol for infrared communications. The following list of infrared codes can be used to program a universal or learning remote control. The Classé Remote Control uses a frequency of 56.0 kHz. Please refer to your remote control's user manual for information on how to program your remote control.

Sys code	IR code	Action
016	1	Change input to input 1
016	2	Change input to input 2
016	3	Change input to input 3
016	4	Change input to input 4
016	5	Change input to input 5
016	6	Change input to input 6
016	7	Change input to input 7
016	8	Change input to input 8
016	9	Change input to input 9
016	10	Go to next input
016	11	Go to previous input
016	12	Toggle Standby/Operate
200	13	Toggle Mute/Unmute
016	14	Info (go to status screen)
016	15	Cycle through display intensities
200	16	Volume up
200	17	Volume down
016	21	Balance (go to balance screen)
200	56	Function key F1
200	57	Function key F2
016	84	Menu
016	85	Home
016	88	Step up (navigate up, +)
016	89	Step down (navigate down, -)
016	90	Step left (navigate left)
016	91	Step right (navigate right)
016	92	Enter
016	120	Change input to input 10
016	121	Change input to input 11
016	122	Change input to input 12
016	123	Change input to input 13
016	124	Change input to input 14
016	125	Change input to input 15

016	126	Change input to input 16
016	127	Change input to input 17
016	128	Change input to input 18
200	134	Function key F3
200	135	Function key F4
200	136	Function key F5
200	137	Function key F6
200	138	Function key F7
200	139	Function key F8
016	150	Set unit to Operate (Turn unit on)
016	151	Set unit to Standby (Turn unit off)
200	152	Set Mute mode on (Mute)
200	153	Set Mute mode off (Unmute)
016	184	Input (go to input select screen)
016	191	Configuration (go to configuration screen)
016	206	Go to next configuration
016	207	Go to previous configuration
016	240	Toggle output 1 on/off
016	241	Toggle output 2 on/off
016	242	Toggle output 3 on/off
016	247	Toggle EQ on/off

CP-800 HEX CODES

RC6 MODE 0, SYSTEM CODE 016

IR CODE 1 TOGGLE 0	INPUT 1
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0032 1275	
IR CODE 1 TOGGLE 1	INPUT 1
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0032 1275	
IR CODE 2 TOGGLE 0	INPUT 2
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
IR CODE 2 TOGGLE 1	INPUT 2
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
IR CODE 3 TOGGLE 0	INPUT 3
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275	
IR CODE 3 TOGGLE 1	INPUT 3
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275	
IR CODE 4 TOGGLE 0	INPUT 4
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 4 TOGGLE 1	INPUT 4
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	

CP-800 HEX CODES

IR CODE 5 TOGGLE 0	INPUT 5
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275	
IR CODE 5 TOGGLE 1	INPUT 5
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275	
IR CODE 6 TOGGLE 0	INPUT 6
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C	
IR CODE 6 TOGGLE 1	INPUT 6
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C	
IR CODE 7 TOGGLE 0	INPUT 7
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 1275	
IR CODE 7 TOGGLE 1	INPUT 7
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 1275	
IR CODE 8 TOGGLE 0	INPUT 8
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 8 TOGGLE 1	INPUT 8
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 9 TOGGLE 0	INPUT 9
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	

CP-800 HEX CODES

IR CODE 9 TOGGLE 1	INPUT 9
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	
IR CODE 10 TOGGLE 0	NEXT INPUT
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 125C	
IR CODE 10 TOGGLE 1	NEXT INPUT
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 125C	
IR CODE 11 TOGGLE 0	PREVIOUS INPUT
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275	
IR CODE 11 TOGGLE 1	PREVIOUS INPUT
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275	
IR CODE 12 TOGGLE 0	STANDBY/OPERATE
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 12 TOGGLE 1	STANDBY/OPERATE
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 125C	
IR CODE 14 TOGGLE 0	INFO
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 14 TOGGLE 1	INFO
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 125C	

CP-800 HEX CODES

IR CODE 15 TOGGLE 0	TOGGLE DISPLAY INTENSITY
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	
IR CODE 15 TOGGLE 1	TOGGLE DISPLAY INTENSITY
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	
IR CODE 21 TOGGLE 0	BALANCE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 1275	
IR CODE 21 TOGGLE 1	BALANCE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 1275	
IR CODE 84 TOGGLE 0	MENU
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C	
IR CODE 84 TOGGLE 1	MENU
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C	
IR CODE 85 TOGGLE 0	HOME
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 1275	
IR CODE 85 TOGGLE 1	HOME
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 1275	
IR CODE 88 TOGGLE 0	CURSOR UP
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0019 0019 125C	

CP-800 HEX CODES

IR CODE 88 TOGGLE 1	CURSOR UP
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0019 125C	
IR CODE 89 TOGGLE 0	CURSOR DOWN
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275	
IR CODE 89 TOGGLE 1	CURSOR DOWN
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275	
IR CODE 90 TOGGLE 0	CURSOR LEFT
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C	
IR CODE 90 TOGGLE 1	CURSOR LEFT
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C	
IR CODE 91 TOGGLE 0	CURSOR RIGHT
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275	
IR CODE 91 TOGGLE 1	CURSOR RIGHT
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275	
IR CODE 92 TOGGLE 0	ENTER
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 125C	
IR CODE 92 TOGGLE 1	ENTER
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 125C	

CP-800 HEX CODES

IR CODE 120 TOGGLE 0	INPUT 10
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 120 TOGGLE 1	INPUT 10
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 121 TOGGLE 0	INPUT 11
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0032 1275	
IR CODE 121 TOGGLE 1	INPUT 11
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0032 1275	
IR CODE 122 TOGGLE 0	INPUT 12
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0031 0019 125C	
IR CODE 122 TOGGLE 1	INPUT 12
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0031 0019 125C	
IR CODE 123 TOGGLE 0	INPUT 13
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 1275	
IR CODE 123 TOGGLE 1	INPUT 13
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 1275	
IR CODE 124 TOGGLE 0	INPUT 14
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	

CP-800 HEX CODES

IR CODE 124 TOGGLE 1	INPUT 14
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	
IR CODE 125 TOGGLE 0	INPUT 15
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0032 0032 1275	
IR CODE 125 TOGGLE 1	INPUT 15
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 0032 1275	
IR CODE 126 TOGGLE 0	INPUT 16
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C	
IR CODE 126 TOGGLE 1	INPUT 16
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C	
IR CODE 127 TOGGLE 0	INPUT 17
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 1275	
IR CODE 127 TOGGLE 1	INPUT 17
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 1275	
IR CODE 128 TOGGLE 0	INPUT 18
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
IR CODE 128 TOGGLE 1	INPUT 18
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	

CP-800 HEX CODES

IR CODE 150 TOGGLE 0	OPERATE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C	
IR CODE 150 TOGGLE 1	OPERATE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C	
IR CODE 151 TOGGLE 0	STANDBY
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275	
IR CODE 151 TOGGLE 1	STANDBY
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275	
IR CODE 184 TOGGLE 0	INPUT SELECT
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 184 TOGGLE 1	INPUT SELECT
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 191 TOGGLE 0	CONFIGURATION SELECT
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 1275	
IR CODE 191 TOGGLE 1	CONFIGURATION SELECT
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 1275	
IR CODE 206 TOGGLE 0	NEXT CONFIGURATION
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C	

CP-800 HEX CODES

IR CODE 206 TOGGLE 1	NEXT CONFIGURATION
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C	
IR CODE 207 TOGGLE 0	LAST CONFIGURATION
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 207 TOGGLE 1	LAST CONFIGURATION
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 240 TOGGLE 0	TOGGLE OUTPUT 1
0000 004A 0000 0014 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 240 TOGGLE 1	TOGGLE OUTPUT 1
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 125C	
IR CODE 241 TOGGLE 0	TOGGLE OUTPUT 2
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275	
IR CODE 241 TOGGLE 1	TOGGLE OUTPUT 2
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 1275	
IR CODE 242 TOGGLE 0	TOGGLE OUTPUT 3
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
IR CODE 242 TOGGLE 1	TOGGLE OUTPUT 3
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0031 0019 125C	

CP-800 HEX CODES

IR CODE 247 TOGGLE 0	TOGGLE EQ
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 1275	
IR CODE 247 TOGGLE 1	TOGGLE EQ
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 1275	

RC6 MODE 0, SYSTEM CODE 200

IR CODE 13 TOGGLE 0	MUTE TOGGLE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275	
IR CODE 13 TOGGLE 1	MUTE TOGGLE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275	
IR CODE 16 TOGGLE 0	VOLUME UP
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 16 TOGGLE 1	VOLUME UP
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 125C	
IR CODE 17 TOGGLE 0	VOLUME DOWN
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	
IR CODE 17 TOGGLE 1	VOLUME DOWN
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	

CP-800 HEX CODES

IR CODE 56 TOGGLE 0	F1
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 56 TOGGLE 1	F1
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
IR CODE 57 TOGGLE 0	F2
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 1275	
IR CODE 57 TOGGLE 1	F2
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 1275	
IR CODE 134 TOGGLE 0	F3
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
IR CODE 134 TOGGLE 1	F3
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
IR CODE 135 TOGGLE 0	F4
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 135 TOGGLE 1	F4
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
IR CODE 136 TOGGLE 0	F5
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C	

CP-800 HEX CODES

IR CODE 136 TOGGLE 1	F5
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 125C	
IR CODE 137 TOGGLE 0	F6
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	
IR CODE 137 TOGGLE 1	F6
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	
IR CODE 138 TOGGLE 0	F7
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0019 125C	
IR CODE 138 TOGGLE 1	F7
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0019 125C	
IR CODE 139 TOGGLE 0	F8
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275	
IR CODE 139 TOGGLE 1	F8
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275	
IR CODE 152 TOGGLE 0	MUTE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 125C	
IR CODE 152 TOGGLE 1	MUTE
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 125C	

CP-800 HEX CODES

IR CODE 153 TOGGLE 0	UNMUTE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275	
R CODE 153 TOGGLE 1	UNMUTE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275	